

VicTrack**Call Logging Unit
Replacement****Telmax 21***Revised: Fri 5 Jun 2009*

There are several things to be changed when replacing a PC based Call Logging Unit. Step 4 is the most important, as there will be no remote access (ie polling) if the password does not match.

1. Login to the replacement CLP as "root"	
2. Set the time and date	eg "date mmddhhmm[yy]"
3. Edit host name with vi in /etc/HOSTNAME	eg "vi /etc/HOSTNAME"
4. Change password for clp user	eg "passwd clp" (get from telmax21/usr/lib/uucp/Systems)
5. Check the files /etc/hosts & /etc/hosts.equiv are setup	
6. Check the speed setting of the PABX port is correct	eg "vi /u/catcom/bin/dopak" then check "stty" line.
7. Reboot system and test for call logging.	

For further information on this procedure Email David Cain

Modem Settings:

NetComm Roadster II profile for use with PC CLU	
ACTIVE PROFILE:	
B0 E0 L0 M1 N1 Q1 T V1 W2 X3 Y0 &C1 &D3 &G0 &J0 &K3 &Q6 &R1 &S1 &T5 &X0 &Y0 S00:003 S01:000 S02:128 S03:013 S04:010 S05:008 S06:004 S07:050 S08:004 S09:006 S10:018 S11:095 S12:050 S18:000 S25:005 S26:001 S36:007 S37:000 S38:000 S46:138 S48:007 S95:000	
STORED PROFILE 0:	
B0 E0 L0 M1 N1 Q1 T V1 W2 X3 Y0 &C1 &D3 &G0 &J0 &K3 &Q6 &R1 &S1 &T5 &X0 S00:003 S02:128 S06:004 S07:050 S08:004 S09:006 S10:018 S11:095 S12:050 S18:000 S36:007 S37:000 S40:104 S41:194 S46:138 S95:000	
STORED PROFILE 1:	
B0 E0 L0 M1 N1 Q1 T V1 W2 X3 Y0 &C1 &D3 &G0 &J0 &K3 &Q6 &R1 &S1 &T5 &X0 S00:003 S02:128 S06:004 S07:050 S08:004 S09:006 S10:018 S11:095 S12:050 S18:000 S36:007 S37:000 S40:104 S41:194 S46:138 S95:000	
TELEPHONE NUMBERS:	
0=	1=
2=	3=
Ensure Modem is programmed at 38400 Baud!	